

Perfect for STEREO

30 WATT AMPLIFIER

- FEATURING THE PATENTED
McINTOSH CIRCUIT
- GUARANTEED 0.5% MAXIMUM
INTERMODULATION DISTORTION
- UNITY COUPLING FOR
PERFORMANCE PLUS



MC-30 \$143.30

McIntosh, the world's most advanced amplifier, is unequalled for quality reproduction of any sound source. Its unique circuitry provides ample reserve power combined with unprecedented low distortion—less than 0.3% harmonic distortion at all frequencies, 20-20,000 cycles and at any volume, even full power!

Designed for those who expect the finest, the McIntosh MC-30 sets a new standard among amplifiers. It brings an almost unbelievable clarity of tone—clean, pure living sound. Most important, you can listen to the McIntosh for hours without listening fatigue or irritation. For performance that really makes a difference, enjoy the McIntosh, masterfully crafted for your lifetime satisfaction.

MC-30 SPECIFICATIONS

Power Supply:	117/125 volts, 50/60 cycles
Power Consumption:	155 watts at 30 watts output 105 watts at zero signal output
Power Output:	30 watts continuous
Input Level:	Input #1 (pin jack and screw terminals) .5 volts to 30 volts, with gain control Input #2 2.5 volts
Frequency Range:	20 to 30,000 cycles $\pm$.1 db at 30 watts output 15 to 50,000 cycles $\pm$.5 db at 30 watts output 10 to 100,000 cycles $\pm$ 1 db at 15 watts output
Harmonic Distortion:	Less than 0.3% at 30 watts output or less, 20 to 20,000 cycles
Intermodulation Distortion:	Less than 0.5% if instantaneous peak power is below 60 watts for any combination of frequencies 20 to 20,000 cycles
Noise and Hum Level:	90 db or more below rated output
Damping Factor:	12 or better for 4, 8 and 16 ohm output, 16 for 600 ohms
Input Impedance:	0.5 meg for 0.5 volt input and 0.13 meg for 2.5 volt input. 20 cycles to 40,000
Output Impedance:	4, 8, 16, 600 ohms (600 ohm is balanced to ground) and 70.7 volts
Phase Shift:	20 cycles 3° 20,000 cycles 9°
Tube Complement:	Rectifier: 5U4-GA; Pre-Amp: 12AX7; Phase Inverter: 12AU7; Voltage Amp: 12BH7; Driver: 12AX7; Output: 2-1614
Size:	13 1/8" x 8" x 8" high
Weight:	30.5 pounds net

McIntosh... the Mark of Excellence

McIntosh *guaranteed* $99\frac{60}{100}\%$ *
perfect amplification!



MC-60 \$198.50

*All but 0.000016 of power output is a perfect reproduction of input signal at 30 watts, 20-20,000 cycles.

FOR THOSE SATISFIED WITH NOTHING BUT THE ULTIMATE IN HIGH FIDELITY, IT'S THE McINTOSH 60 WATT AMPLIFIER — UNSURPASSED FOR PERFORMANCE AND QUALITY.

This unique instrument sets a standard of excellence in amplification, for it has reached the theoretical limit of quality and efficiency. The McIntosh MC-60 amplifier, with patented circuit, is the only power amplifier which will produce 60 watts of power at less than 0.3% distortion from 20 to 20,000 cycles per second. This measurement insures the complete absence of discordant tones, and provides the purest and most perfect amplification available. There is no

increase in distortion even when extra power is demanded by program material. Since nothing is added to or taken from the input signal, clean, unparalleled reproduction of sound results, bringing out an exquisite realism at low, as well as high, volume levels . . . clear lucid highs, with no peaking; natural, full bass with no booming; thrilling middle range, all there with the McIntosh.

In reproducing music or speech with complete realism, the exceptional reserve power capacity of the MC-60 is called upon, for many short intervals per second, even at moderate volume, to re-create faithfully and accurately all the fundamentals, harmonics and overtones present in natural sounds.

YOUR FRANCHISED McINTOSH DEALER PROUDLY RECOMMENDS AND DISPLAYS
McINTOSH EQUIPMENT

McIntosh
LABORATORY, INC.

4 Chambers St., Binghamton, N. Y.

IN CANADA: MANUFACTURED BY McCURDY RADIO INDUSTRIES, LTD.,
22 FRONT STREET WEST, TORONTO, CANADA