

# RX-400A

AM / FM STEREO RECEIVER



- All Solid State Design with Silicon Output Transistors.
- FET Front End Tuner.
- Ceramic Filter.
- Rotary Controls: Dual Bass, Dual Treble, Balance, Volume, Function Selector and Tuning.
- Push Buttons: Power, Speaker 1, Speaker 2, Mode, Tape Monitor and Loudness.
- Illuminated Dual Purpose Signal Strength/ FM Center Tuning Meter.
- Illuminated Dial Board.
- Stereo Indicator Light.
- Function Indicator Lights.
- Front Panel Headphone Jack.
- Rear Panel Speaker Matrix Switch for simulated 4-Channel.
- Pre-Amp Outputs and Main-Amp Inputs.
- Handsome Wood Cabinet.

#### TUNER SECTION:

- FM — Sensitivity (IHF):  $2.5\mu\text{V}$
- Harmonic Distortion: less than 1%
- S/N: better than 60 db
- IF Rejection: better than 70 db
- Stereo Separation: 35 db.
- AM — Sensitivity (IHF):  $30\mu\text{V}$
- Image Rejection: 40 db.

#### AMPLIFIER SECTION:

- Total Music Power (IHF): 80W ( $4\Omega$ ), 50W ( $8\Omega$ )
- Continuous Power (RMS): 22W/Ch ( $4\Omega$ ), 20W/Ch ( $8\Omega$ )
- Harmonic Distortion: 0.2%
- IM Distortion: 0.4%
- Frequency Response: 15 — 50 kHz
- Power Bandwidth (IHF): 25 — 30 kHz
- Speaker Impedance: 4, 8, 16 $\Omega$
- Power Voltage: AC 100, 117, 220, 240V
- 50/60 Hz
- Dimensions: 17-1/8" (W) x 5" (H) x 12-1/2" (D)
- Weight: 15.4 lbs/7 kg.