



SANSUI QRX 3500 AM/FM/MPX 4 Channel Receiver

- QS Regular Matrix.
- QS Vario-Matrix decoding all Regular Matrix records, converting 2 Channel Stereo records and FM broadcasts into Authentic 4 Channel Sound.
- Phase Matrix including front-rear logic circuitry to decode all SQ encoded records.
- Facilities for connecting up to two 4 Channel and one 2 Channel Tape Deck with tape-to-tape dubbing and monitoring.

Technical Specification

AUDIO SECTION

Continuous power at 8 ohms (each channel driven) 22 W x 4; Harmonic distortion 0.5%; IM distortion 0.5%; Power bandwidth (IHF) 10-33,000 Hz; Load impedance 4-16 ohms; Damping factor (8 ohms) 30; Input sensitivity:- PHONO 2.5 mV, AUX 150 mV, Tape Mon (Pin) (DIN) 150 mV.

Recording output:- Tape REC (Pin) 150 mV, Tape REC (DIN) 30 mV. Hum and noise (IHF) AUX 75 dB.

Controls and switches:- Bass control ± 12 dB/50 Hz; Treble control ± 12 dB/15 kHz; Loudness +8 dB/50 Hz, +3 dB/10 kHz; Low filter -10 dB/50 Hz; High filter -10 dB/10 kHz.

TUNER SECTION

FM (88 to 108 MHz):- Sensitivity (IHF) 2.2 μ V; S/N ratio 65 dB; Selectivity 50 dB; Capture ratio (IHF) 2 dB; Image frequency rejection 75 dB; IF rejection 90 dB; Stereo separation 35 dB, AM (535 to 1605 kHz); Sensitivity (Bar Antenna) 50 dB/m; Selectivity 25 dB.

Rec. Ret. Price (inc. VAT) £373.63 **Comet Price (inc. VAT) £298.90**

Hofkamp & van Droffelaar

*Specialisten in vintage HiFi en analoge camera techniek
met eigen technische dienst.*

Jan G. Hofkamp
Hoornsedijk 9
9752 XJ Haren

050 - 534 15 06
06 - 38 18 34 64
info@dehofkeuken.nl